

Product Nexus Max Monitor

Product Code: NGM-41-FSK

Description: Bed exit monitor alerts caregiver to patient activity; wireless link to sensorpads, pendant, floor mat, or motion sensor. Works with Nexus

Features:

- Works with up to 3 wireless devices
- Pause/Vol & reset control on monitor face
- Convenient On/Off switch on left side
- 6.3mm audio output to trigger nurse call
- Tx On/Off switch in battery compartment
- Normally open output through 6.3mm audio port
- Operates on batteries or AC adaptor
- Low battery and change pad notification
- Input lost notification (pad lost, nurse call)
- Wireless LoRa output for use with Nexus

Works with:

- Wireless bed, chair, and floor sensor mats
- TXP-11(V2) Wristband Transmitter
- PIR-21 Wireless Motion Sensor
- UT-11 Universal Transmitter Door Sensor
- PC-40 Protective Cover (included)
- BKT-10 Wall Mount Bracket (included)
- ILB-21-EXT LoRa Range Extender
- DON-30-FSK LoRa Receiver Dongle



Technical Specifications

Receiver: 433.92 MHz
 Transceiver: 434.4 MHz (LoRa)
 Operating range: 80m (line of sight)
 Power supply: 5~6V DC, 300mA
 or 3 x AA-type alkaline batteries
 Battery life: 6 months (Nominal)
 Dimensions: 120 x 83 x 35mm (w/ cover)
 Housing material: ABS (UL-94HB)
 Net weight: 210g (w/ cover)
 Operating temp.: 5°C ~ 40°C
 Rel. humidity: < 85%

Standards

RED EN 300220-1&2,
 EN 301489-1&3
 Safety: EN 50663
 EN 62479
 EN 62368-1
 Medical Device
 Immunity: EN 60601-1-2
 Manufacture: ISO 9001:2015,
 ISO 13485:2016
 FCCID: WNG-NGM-41-FSK
 UKCA